



**HAL**  
open science

## Multi-Source Cognitive BackCom with Temporal Combining for Reliable IoT Communication

Richard B Nti, Derek Kwaku Pobi Asiedu, Mustapha Benjillali, Ji-Hoon Yun,  
Samir Saoudi

► **To cite this version:**

Richard B Nti, Derek Kwaku Pobi Asiedu, Mustapha Benjillali, Ji-Hoon Yun, Samir Saoudi. Multi-Source Cognitive BackCom with Temporal Combining for Reliable IoT Communication. CTW 2024: IEEE Communication Theory Workshop, May 2024, Banff, Canada. hal-04599969

**HAL Id: hal-04599969**

<https://imt-atlantique.hal.science/hal-04599969v1>

Submitted on 4 Jun 2024

**HAL** is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

# Multi-Source Cognitive BackCom with Temporal Combining for Reliable IoT Communication

Richard B. Nti\*, Derek K. P. Asiedu†, Mustapha Benjillali†§, Ji-Hoon Yun\*, and Samir Saoudi†

\*Department of Electrical and Information Engineering, SeoulTech, 01811 Seoul, South Korea.

Emails: richardnti@seoultech.ac.kr, and jhyun@seoultech.ac.kr

†IMT-Atlantique, Lab-STICC, 29238 Brest, France. Emails: kwakupobi@ieee.org, and samir.saoudi@imt-atlantique.fr

§Department of Communication Systems, INPT, 10100 Rabat, Morocco. Email: benjillali@ieee.org

**Abstract**—Backscatter communication has evolved over the years, but the research interest has predominantly focused on single carrier radio frequency source. In this paper, we seek to utilize the accessibility of multiple carrier sources to boost backscatter communication reliability. Under the framework of utilizing temporal combining, we show the bit error rate gain of our proposed bit-stream decoding scheme over the traditional approach through analysis and simulation.

**Index Terms**—Backscatter communication (BackCom), multi-carrier sources, temporal combining (TC), repetition coding.

## I. INTRODUCTION

Internet-of-Things networks (IoTNs) have grown in popularity over recent years due to their potential to enable human-environment digital interactions [1]. Backscatter (BC) communication (BackCom) is a battery-less wireless communication technology for IoT devices, where the BC device reflects/absorbs a radio frequency (RF) signal emitted by a nearby source to convey its data on this signal.

This paper proposes a multi-source temporal combining (TC) solution for bit-stream decoding to enhance the reliability of BackCom in cognitive radio networks (CRNs), where primary transmitters (PTs) serve as carrier sources and BackCom devices are secondary transmitters (STs). Unlike previous research works on TC [2], [3], which primarily focused on a single RF source, our solution leverages multiple PTs to exploit increased transmission opportunities for TC. Our simulation results demonstrate the effectiveness of exploiting multiple sources in further enhancing BackCom reliability.

## II. SYSTEM MODEL

In the CRN system model shown in Fig. 1,  $K$  single-antenna PTs ( $\{T_k\}_{k=1}^K$ ) (i.e., RF multi-carrier sources) and an  $M$ -antenna BackCom tag ( $T_{g_1}$ ) coexist and share spectrum. An  $N$ -antenna receiver ( $R_1$ ) decodes both the PT data and the BackCom data within received signals. The following assumptions are made within this work concerning system operations: (i) All PTs are Wi-Fi devices with different transmission packet lengths and topological locations from  $R_1$ , and there are direct links between the PTs and  $R_1$ ; (ii)  $T_{g_1}$  uses the PTs RF signals for BackCom; (iii) The PTs transmit data orthogonally in the time domain using carrier sensing.

The  $T_k$ -to- $T_{g_1}$  channels are denoted as  $\mathbf{h}_k$ ,  $T_k$ -to- $R_1$  channel is given as  $\mathbf{f}_k$  and the  $T_{g_1}$ -to- $R_1$  channel is defined as  $\mathbf{g}_{R_1}$ ,




Fig. 1: BackCom with multiple carrier sources.

and the total PTs transmit time is denoted as  $S = \sum_{k=1}^K \alpha_k$ , where  $\alpha_k$  is the airtime of  $T_k$ -to- $R_1$  transmission.  $P_k$  and  $x_k(t_k)$  are  $T_k$ 's transmit power and instantaneous transmitted symbol at time  $t_k$ , respectively.  $T_{g_1}$ 's data symbol is defined as  $x_{g_1}(t_k)$ . During  $\alpha_k$ , received  $T_k$  signal at  $T_{g_1}$  is given by

$$y_{k,g_1}(t_k) = \sqrt{P_k} \mathbf{h}_k x_k(t_k) + n_{g_1}(t_k), \quad (1)$$

where  $\mathbb{E}[|x_k(t_k)|^2] \triangleq 1$  and  $n_{g_1}(t_k) \sim \mathcal{CN}(0, \sigma_{g_1}^2)$  denotes additive white Gaussian noise (AWGN) with power  $\sigma_{g_1}^2$  at  $T_{g_1}$ . The  $T_k$  signal received by  $R_1$  is defined as

$$y_{k,R_1}(t_k) = \sqrt{P_k} \eta \mathbf{h}_k x_k(t_k) x_{g_1}(t_k) \mathbf{g}_{R_1} + \sqrt{P_k} x_k(t_k) \mathbf{f}_k + n_{R_1}(t_k), \quad (2)$$

where  $\mathbb{E}[|x_{g_1}(t_k)|^2] \triangleq 1$ ,  $n_{R_1}(t_k) \sim \mathcal{CN}(0, \sigma_{R_1}^2)$  is the AWGN at  $R_1$ , and  $\eta$  is the reflection attenuation coefficient. For TC,  $T_{g_1}$  repeats the transmission of the same data packet over the duration  $S$ . Thus, the series  $x_{g_1}(t)$  remains unchanged throughout  $S$ .

## III. RECEIVER DESIGN AND TEMPORAL COMBINING

### A. Linear Detectors under Frequency-Shift Technique

$T_{g_1}$  utilizes the frequency-shift technique (FST), wherein  $R_1$  captures two valid Wi-Fi signals, one on the carrier-signal channel and the other on the shifted channel, with a separation equal to the channel bandwidth.  $R_1$  first decodes these received signals employing linear detection, as described below. The linear detectors under consideration are the maximal-ratio combining (MRC), the zero-forcing (ZF) and the minimum mean-squared-error (MMSE), which are defined as

$$\mathbf{w}_{k,R_1} = \begin{cases} \frac{\tilde{\mathbf{g}}_{k,R_1}}{\|\tilde{\mathbf{g}}_{k,R_1}\|^2}, & \text{for MRC} \\ \left( (\tilde{\mathbf{g}}_{k,R_1})^H \tilde{\mathbf{g}}_{k,R_1} \right)^{-1} (\tilde{\mathbf{g}}_{k,R_1})^H, & \text{for ZF} \\ \left( (\tilde{\mathbf{g}}_{k,R_1})^H \tilde{\mathbf{g}}_{k,R_1} + \frac{\sigma^2}{P_k} I \right)^{-1} (\tilde{\mathbf{g}}_{k,R_1})^H, & \text{for MMSE} \end{cases} \quad (3)$$

for detecting the  $T_k$  signal, where  $\tilde{\mathbf{g}}_{k,R_1} = \sqrt{\eta} \mathbf{h}_k \mathbf{g}_{R_1}$  and  $I$  represents an identity matrix. By applying any of the above receiver designs, the bit-streams of the  $T_k$  and  $T_{g_1}$  signals can be extracted, respectively, as

$$\hat{x}_k(t_k) = \arg \max_{x_k(t_k) \in \mathbf{A}_{s,k}} |x_k(t_k) - y_{k,R_1}(t_k) \mathbf{w}_{k,R_1}^H|, \quad (4)$$

$$\hat{x}_{g_1}(t_k) = \arg \max_{x_{g_1}(t_k) \in \mathbf{A}_c} \left| x_{g_1}(t_k) - \frac{y_{k,R_1}(t_k) \mathbf{w}_{k,R_1}^H}{\hat{x}_k(t_k)} \right|, \quad (5)$$

where  $\{\mathbf{A}_{s,k}, \mathbf{A}_c\}$  are  $\{T_k, T_{g_1}\}$  symbol set, respectively [4]. Then,  $R_1$  applies XOR operation on these two data bits, which finally leads to the extraction of  $K$  BackCom bit-streams.

### B. Multi-Source Temporal Combining

Let  $\mathcal{B} = \{B_1, \dots, B_K\}$  represent the set of acquired BackCom bit-streams. Note that the length of  $B_k$  is the same as  $L_k$ . Without loss of generality, we assume  $L_1 < \dots < L_K$ . The multi-source TC scheme is applied to  $\mathcal{B}$  in three steps: (i) The bit-streams are partitioned into smaller blocks based on their lengths. Each block includes an equal number of bits from each bit-stream, starting from the first bit up to  $L_1$  in the first block, and continuing incrementally up to  $L_K$ . (ii) The scheme verifies if the number of received bit-streams in each block is odd, for majority voting. If not, the bit-stream with the minimum original length is excluded from the block. (iii) Within each block, bitwise majority voting is performed to determine the status of each bit as data-one or data-zero. Let  $\mathcal{C} = \{\mathcal{C}_1, \dots, \mathcal{C}_K\}$  denote the set of blocks, where  $\mathcal{C}_k$  is the  $k$ th block containing corresponding segments of the bit-streams. Earlier blocks, comprising more bit sequences for TC, will result in fewer bit errors, while later blocks, with fewer bit sequences, may result in higher bit errors. Note that the voting process is not applied to the standalone block (last block). Finally, the voting results from individual blocks are concatenated in sequence, yielding the BackCom data.

The bit error rate (BER) after TC is obtained as follows. Assume that before TC, i.i.d. bit errors with probability  $p_b$  occur across bits in the bit-streams. Let the cardinality of  $\mathcal{C}_k$  be denoted by  $C_k$ , which is obtained as  $\lceil (k+1)/2 \rceil \times 2 - 1$ . Then, the BER after TC at the  $\ell$ th bit, denoted by  $p_{b,\ell}$ , where  $L_{k-1} < \ell \leq L_k$ , is given by

$$p_{b,\ell} = \sum_{j=\lceil C_k/2 \rceil}^{C_k} \binom{C_k}{j} (1-p_b)^j p_b^{C_k-j}. \quad (6)$$

This demonstrates two important points. First, as  $C_k$  increases,  $p_{b,\ell}$  decreases, indicating that exploiting more carrier sources for TC leads to increased reliability of BackCom. Second, since  $C_1 \leq \dots \leq C_K$ , we have  $p_{b,1} \leq \dots \leq p_{b,L_K}$ . Thus, the BackCom data after multi-source TC may experience higher BER at later bits, as fewer bit sequences remain to combine. This suggests the need for more reliable transmission schemes (e.g., coding) for later BackCom bits, which we leave for future work.




Fig. 2: BER performance of multi-source TC over distance.

## IV. SIMULATION AND DISCUSSION

The simulation environment is implemented in MATLAB to emulate the PHY layer of the IEEE 802.11n configuration with a channel bandwidth of 20 MHz, a payload size of 500 bytes, and employing binary convolutional coding. The delay profile of Model-D is employed, while the remaining parameters follow the WLAN HT (high throughput) format for waveform generation. The simulation includes pathloss and AWGN, with  $M = N = 2$ , and considers a non-line-of-sight (NLOS) distance of 20m in Rayleigh fading channels. Two cases are examined: TC-3 and TC-5, corresponding to scenarios with 3 and 5 PTs, respectively.

We evaluate the BER performance of the proposed multi-source TC scheme with the three linear detectors, considering a fixed SNR of 13 dB. As shown in Fig. 2, the difference in BER between the traditional approach (without TC) and TC-3 remains marginal as the Tag-to-Rx distance increases, whereas a noticeable gap emerges for TC-5. On average, TC-3 demonstrates a 15.79% improvement in BER, while TC-5 achieves approximately 42.85% enhancement compared to the traditional method.

## V. CONCLUSION

The utilization of multiple carrier sources within the TC framework has resulted in notable improvements in BER performance for BackCom. Specifically, our proposed scheme, evaluated with three linear detectors, demonstrated a substantial enhancement ranging from 15% to 42%.

## REFERENCES

- [1] A. Khanna and S. Kaur, "Internet of things (IoT), applications and challenges: A comprehensive review," *Wireless Personal Communications*, vol. 114, pp. 1687–1762, May 2020.
- [2] H. Hwang, R. B. Nti, and J.-H. Yun, "Spectro-temporal combining in bistate WiFi backscatter communication with frequency shift," *IEEE Access*, vol. 9, pp. 113 735–113 747, Aug. 2021.
- [3] R. B. Nti, D. K. P. Asiedu, and J.-H. Yun, "Nonsequential link adaptation using repetition codes for Wi-Fi backscatter communication," *IEEE Trans. Veh. Technol.*, pp. 1–6, Jan. 2024.
- [4] Y.-C. Liang, Q. Zhang, E. G. Larsson, and G. Y. Li, "Symbiotic radio: Cognitive backscattering communications for future wireless networks," *IEEE Trans. Cog. Commun. Network.*, vol. 6, no. 4, pp. 1242–1255, Sep. 2020.